PHASE SEQUENCE: YOU DO NOT NEED A SPECIAL INSTRUMENT

DO YOU NEED A SPECIAL INSTRUMENT?

Guidance Note 3 · p.93 . Phase sequencing is done at **each point** of the installation, to confirm every conductor is in the right place.

METHOD	HOW
By inspection	Brown lands where brown belongs, through the busbar, at every point
By continuity	With the circuit isolated, test between two line conductors as you would an $R_1 + R_2$, then the next pair, then the last
With an AVI	The rotation test — below

THE PROBE SEQUENCE

The two probe tips are labelled **L1** and **L2**.

1. L1 probe → L1 L2 probe → L2
2. L1 probe → L2 L2 probe → L3
3. L1 probe → L3 L2 probe → L1

You want the **R** arrow lighting up on all three.

✋ **The AVI rotation check is a live test.** You are working on a live three-phase board. Treat it accordingly. Only the continuity method is done dead.

Free section from Sparky Study Notes. The full Level 3 notes, 1,463 practice questions and the video lessons: sparkystudynotes.co.uk